

Anritsu envision : ensure

USB Power Sensor

MA24106A

50 MHz to 6 GHz



Introduction

The MA24106A power sensor is a highly accurate instrument that communicates with a PC using the Universal Serial Bus interface (USB). Its measurement capability mimics a traditional thermal (thermo-electric) power sensor, but has a wider dynamic range. This makes the MA24106A ideal for measuring average power of CW, multi-tone, and modulated RF waveforms such as 3G, 4G, and OFDM.

The MA24106A measures true RMS power regardless of the type or bandwidth of the input signal.

Features

- True RMS detection over a 63 dB dynamic range enables accurate CW and modulated power measurements
- Ready for use in a wide variety of applications, including installation and maintenance of base stations, testing of 3G and 4G products, cell phones, and general purpose RF devices
- High damage power levels and ESD protection provides ruggedness and reliability
- Low current consumption (100 mA) preserves laptop battery life
- Eliminating the need for a reference calibrator reduces test time and handling in production
- Light weight, economical, and easy to use with a desktop or laptop PC
- One year calibration cycle and worldwide service centers ensure reduced downtime
- Compatible with most Anritsu RF and microwave handheld analyzers
(In some cases, the high accuracy power meter software option (Option 19 is required)
- Complimentary PowerXpert™ PC application for easy sensor control and data analysis

Table of Contents

Definitions.....3
 General Specifications4
 Model.....5
 Included Accessories.....5
 Available Options.....5
 Optional Accessories.....6

Definitions

All specifications and characteristics apply under the following conditions, unless otherwise stated:

Warm-Up Time	After 20 minutes of warm-up time, where the instrument is left in the on state. One-hour warm up with no operation when measured with 128 averages for one hour keeping temperature within ± 1 °C.
Uncertainty	Expanded uncertainty with K=2 for absolute power measurements on CW signal at 0 dBm calibration level from 50 MHz to 6 GHz. Expanded uncertainty with K=2 after zero operation when measured with 128 averages for 5 minutes. In high aperture time mode, noise is 1.3 nW and 0.3 μ W in Range 1 and Range 2 respectively.
Calibration Cycle	Recommended calibration cycle is 12 months. All specifications subject to change without notice. For the most current data sheet, please visit the Anritsu web site: www.anritsu.com .

General Specifications

Sensor		
Frequency Range	50 MHz to 6 GHz	
Dynamic Range	-40 dBm to +23 dBm	
Input Return Loss	> 26 dB (50 MHz to < 2 GHz) > 20 dB (2 GHz to 6 GHz)	
Measurement Ranges	Range 1, -40 dBm to -5 dBm Range 2, -5 dBm to +23 dBm	
Signal Channel Bandwidth	100 Hz, typical	
Measurement Uncertainty		
Linearity	± 0.13 dB (power level < +18 dBm) ± 0.18 dB (power level \geq +18 dBm)	
Calibration Factor ¹	± 0.035 dB	
Noise ²	< 2.5 nW (-40 dBm to -5 dBm) < 0.6 μ W (-5 dBm to +23 dBm)	
Zero Set	< 10 nW (-40 dBm to -5 dBm) < 1.7 μ W (-5 dBm to +23 dBm)	
Zero Drift ³	< 3.0 nW (-40 dBm to -5 dBm) < 0.5 μ W (-5 dBm to +23 dBm) _r	
Temperature Compensation ⁴	± 0.06 dB (at 0 °C to 50 °C)	
Effect of Digital Modulation ⁴	± 0.02 dB (power level < +18 dBm) ± 0.10 dB (power level \geq +18 dBm)	
System		
Measurand	True-RMS / Average power	
Measurement Resolution	0.01 dB	
Offset Range	± 100 dB	
Averaging Range	1 to 256	
Measurement Speed	10 measurements per second, typical (one measurement per second, typical in high aperture time mode.)	
Range	Auto-ranging between Range 1 and Range 2	
Interface	USB 2.0	
Host Operating System (PowerXpert application compatibility)	Microsoft® Windows® 7, Windows Vista, Windows XP, Windows 2000, Windows 8, and Windows 10	
Micro Processor	Intel® Pentium® III with 1 GB RAM or Intel® Pentium® IV with 512 MB RAM, or equivalent (Intel® Pentium® IV with 1 GB RAM recommended)	
Supporting Software	Microsoft® .NET 3.5	
Disc Space	100 MB hard-disk free space	
Display	Display resolution 1024 × 768	
USB Port	USB 2.0 full-speed (compatible with USB 1.0 and 1.1) interface	
General		
Current (via host USB Mini-B)	100 mA (typical) at 5 V (150 mA maximum)	
Maximum DC Voltage at RF Port	± 25 V	
Maximum CW Power	+ 33 dBm	
Size	60.4 mm x 22.2 mm x 84.2 mm typical (2.37 in x 0.87 in x 3.31 in) (Not including N connector.)	
Weight	180 grams typical (6.4 oz)	
Regulatory Compliance		
European Union	EMC 2014/30/EU, EN 61326:2013, CISPR 11/EN 55011, IEC/EN 61000-4-2/3/4/5/6/8/11 Low Voltage Directive 2014/35/EU Safety EN 61010-1:2010 RoHS Directive 2011/65/EU	
Australia and New Zealand	RCM AS/NZS 4417:2012	
South Korea	KCC-REM-A21-0004	
Environmental		
(Tests were performed per MIL-PRF-28800F (Class 3))		
Operating Temperature	0 °C to 50 °C	
Storage Temperature	-51 °C to 71 °C	
Maximum Relative Humidity	45% relative humidity at 55 °C (non-condensing) 75% relative humidity at 40 °C (non-condensing) 95% relative humidity at 30 °C (non-condensing)	
Mechanical Shock	30 g _n half-sine, 11 ms duration	
Vibration	Sinusoidal: 5-55 Hz, 3 g max Random: 10-500 Hz, power spectral density 0.03 g ² /Hz	

- Expanded uncertainty with K=2 for absolute power measurements on CW signal at 0 dBm calibration level from 50 MHz to 6 GHz.
- Expanded uncertainty with K=2 after zero operation when measured with 128 averages for 5 minutes. In high aperture time mode, noise is 1.3 nW and 0.3 μ W in range 1 and range 2 respectively.
- After one hour warm-up and zero operation. Measured with 128 averages for one hour keeping the temperature within ± 1 °C.
- Measurement error with reference to a CW signal of equal power and frequency at 25 °C

Model

Part Number	Description
MA24106A	True-RMS USB Power Sensor, 50 MHz to 6 GHz

Included Accessories

Part Number	Description
2000-1566-R	1.8 meters USB A to Mini-B cable
10585-00021	Quick Start Guide

Available Options

Part Number	Description
MA24106A-097	Option 97, Accredited Calibration to ISO17025 and ANSI/NCSL Z540. Test report and uncertainty data included.
MA24106A-098	Option 98, Standard calibration to ISO17025 and ANSI/NCSL Z540.
MA24106A-099	Option 99, Premium calibration to ISO17025 and ANSI/NCSL Z540. Test report and uncertainty data included.

Optional Accessories

Calibration Torque Wrenches

Part Number	Description
2000-1593-R	3 meters USB A to Mini-B cable
2000-1594-R	5 meters USB A to Mini-B cable
01-200	Calibrated torque wrench for N connector
01-204	Calibrated torque wrench for K and V connectors

Power Attenuators (Recommended for cable and antenna line sweep applications only. Not recommended for low PIM.)

Part Number	Description
3-1010-123	N(m) to N(f), DC to 8.5 GHz, 30 dB, 50 W, 50 Ω
3-1010-124	N(m) to N(f), DC to 8.5 GHz, 40 dB, 100 W, 50 Ω
3-1010-122	N(m) to N(f), DC to 12.4 GHz, 20 dB, 5 W, 50 Ω
42N50-20	N(m) to N(f), DC to 18 GHz, 20 dB, 5 W, 50 Ω
42N50-30	N(m) to N(f), DC to 18 GHz, 30 dB, 50 W, 50 Ω

Precision Coaxial Adapters



Part Number	Description
510-90	N(m) to 7/16 DIN(f), DC to 3.3 GHz
510-91	N(f) to 7/16 DIN(f), DC to 3.3 GHz
510-92	N(m) to 7/16 DIN(m), DC to 3.3 GHz
510-93	N(f) to 7/16 DIN(m), DC to 3.3 GHz
33N50B	N(f) to N(f), DC to 18 GHz
33N50B	N(m) to N(f), DC to 18 GHz
33N50B	N(m) to N(m), DC to 18 GHz
34AN50	GPC-7 to N(m), DC to 18 GHz
34ANF50	GPC-7 to N(f), DC to 18 GHz
34NFK50	N(f) to K(m), DC to 18 GHz
34NFKF50	N(f) to K(f), DC to 18 GHz
34NK50	N(m) to K(m), DC to 18 GHz
34NKF50	N(m) to K(f), DC to 18 GHz

Sensor Calibration Utility

Part Number	Description
2300-528	MA24106A CalXpert™

Training at Anritsu

Anritsu has designed courses to help you stay up to date with technologies important to your job. For available training courses, visit: www.anritsu.com/training



• United States

Anritsu Americas Sales Company
450 Century Parkway, Suite 190
Allen, TX 75013, U.S.A.
Phone: +1-800-Anritsu (1-800-267-4878)

• Canada

Anritsu Electronics Ltd.
700 Silver Seven Road, Suite 120
Kanata, Ontario K2V 1C3, Canada
Phone: +1-613-591-2003
Fax: +1-613-591-1006

• Brazil

Anritsu Eletronica Ltda.
Praça Amadeu Amaral, 27 - 1 Andar
01327-010 - Bela Vista - Sao Paulo - SP
Brazil
Phone: +55-11-3283-2511
Fax: +55-11-3288-6940

• Mexico

Anritsu Company, S.A. de C.V.
Blvd Miguel de Cervantes Saavedra #169 Piso 1,
Col. Granada
Mexico, Ciudad de Mexico, 11520, MEXICO
Phone: +52-55-4169-7104

• United Kingdom

Anritsu EMEA L td.
200 Capability Green
Luton, Bedfordshire, LU1 3LU, U.K.
Phone: +44-1582-433200
Fax: +44-1582-731303

• France

Anritsu S.A.
12 avenue du Québec, Bâtiment Iris 1- Silic 612,
91140 Villebon-sur-Yvette, France
Phone: +33-1-60-92-15-50
Fax: +33-1-64-46-10-65

• Germany

Anritsu GmbH
Nemetschek Haus, Konrad-Zuse-Platz 1
81829 München, Germany
Phone: +49-89-442308-0
Fax: +49-89-442308-55

• Italy

Anritsu S.r.l.
Via Elio Vittorini 129, 00144 Roma, Italy
Phone: +39-6-509-9711
Fax: +39-6-502-2425

List Revision Date: 20181114

• Sweden

Anritsu AB
Isafjordsgatan 32C
164 40 Kista, Sweden
Phone: +46-8-534-707-00

• Finland

Anritsu AB
Teknobulevardi 3-5
FI-01530 Vantaa, Finland
Phone: +358-20-741-8100
Fax: +358-20-741-8111

• Denmark

Anritsu A/S
Torveporten 2
2500 Valby, Denmark
Phone: +45-7211-2200
Fax: +45-7211-2210

• Russia

Anritsu EMEA Ltd.
Representation Office in Russia
Tverskaya str. 16/2, bld. 1, 7th floor
Moscow 125009, Russia
Phone: +7-495-363-1694
Fax: +7-495-935-8962

• Spain

Anritsu EMEA Ltd.
Representation Office in Spain
Paseo de la Castellana, 141. Planta 5
Edificio Cuzco IV
28046 Madrid, Spain
Phone: +34-915-726-761
Fax: +34-915-726-621

• United Arab Emirates

Anritsu EMEA Ltd.
Dubai Liaison Office
902 Aurora Tower
P O Box: 500311 - Dubai Internet City
Dubai, United Arab Emirates
Phone: +971-4-3758479
Fax: +971-4-4249036

• India

Anritsu India Private Limited
6th Floor, Indiqube ETA, No.38/4
Adjacent to EMC2, Doddanekundi, Outer Ring Road
Bengaluru 560048, India
Phone: +91-80-6728-1300
Fax: +91-80-6728-1301

• Singapore

Anritsu Pte. Ltd.
11 Chang Charn Road, #04-01, Shriro House
Singapore 159640
Phone: +65-6282-2400
Fax: +65-6282-2533

• P.R. China (Shanghai)

Anritsu (China) Co., Ltd.
Room 2701-2705, Tower A
New Caohejing International Business Center
No. 391 Gui Ping Road
Shanghai 200233, P.R. China
Phone: +86-21-6237-0898
Fax: +86-21-6237-0899

• P.R. China (Hong Kong)

Anritsu Company Ltd.
Unit 1006-7, 10/F.
Greenfield Tower, Concordia Plaza
No. 1 Science Museum Road
Tsim Sha Tsui East, Kowloon
Hong Kong, P.R. China
Phone: +852-2301-4980
Fax: +852-2301-3545

• Japan

Anritsu Corporation
8-5, Tamura-cho, Atsugi-shi, Kanagawa, 243-0016
Japan
Phone: +81-46-296-6509
Fax: +81-46-225-8352

• South Korea

Anritsu Corporation, Ltd.
5FL, 235 Pangyojeok-ro
Bundang-gu, Seongnam-si
Gyeonggi-do 13494, South Korea
Phone: +82-31-696-7750
Fax: +82-31-696-7751

• Australia

Anritsu Pty. Ltd.
Unit 20, 21-35 Ricketts Road
Mount Waverley, Victoria 3149, Australia
Phone: +61-3-9558-8177
Fax: +61-3-9558-8255

• Taiwan

Anritsu Company Inc.
7F, No. 316, Sec. 1, NeiHu Rd, Taipei 114, Taiwan
Phone: +886-2-8751-1816
Fax: +886-2-8751-1817